AUSPROTEC™

Reduce your stock holdings and down time today



6 - 32 VOLT LED PILOT LIGHTS

The PowerLight™ Multi Voltage LED Pilot Lights have been designed to consolidate all No Load LED's under four easy to use part numbers.

With an operating range of 6 – 32 volts DC, these units have been specifically designed to operate in the harshest conditions. They are compact in design and are highly resistant to vibration, dust and moisture.

Their reliability helps to eliminate costly downtime caused by the regular replacement of standard incandescent globes, often used as indicators. LED pilot lights are far more tolerant to changes in voltage and voltage spikes.

Please Note: If a loaded LED Pilot Light is required (for alternator excitation) a resistor assembly needs to be applied across the power and ground.



Features

- Operating Range: 6 – 32 Volts DC
- Current Draw: 20ma @ 12 VDC, 22ma @ 24 VDC
- Minimum Start to Glow: 2.79 VDC
- Bi-directional polarity
- Available in Red, Blue, Green and Yellow
- Modern Illumination
- 6.3mm spade termination
- Fully encapsulated and vibration resistant
- No internal filament extending operating life and reducing downtime
- Cost effective replacement for standard pilot lights

Specifications

Thread diameter:	16mm
Fits hole diameter:	17-20mm
Spade terminal:	6.3mm
Fits panel thickness:	up to 20mm

Parts

APN: 2504	24V RESISTOR EXCITATION ASSEMBLY
APN: 8751	12V RESISTOR EXCITATION ASSEMBLY
APN: 11109	LED PILOT LIGHT 6 - 32V 2 TERMINAL RED
APN: 11110	LED PILOT LIGHT 6 - 32V 2 TERMINAL GREEN
APN: 11111	LED PILOT LIGHT 6 - 32V 2 TERMINAL YELLOW
APN: 11112	LED PILOT LIGHT 6 - 32V 2 TERMINAL BLUE

Reference: SBAP0513060

RCT
Head Office

Unit 1-5/511 Abernethy Rd
Kewdale WA 6105, Australia

sales@rct-global.com

Australia +61 8 9353 6577
Africa +27 83 292 4246
Canada +1 705 590 4001
Central Asia +7 910 411 1174
USA +1 801 938 9214
South America +56 22 4423 6600

Copyright © 2023 Remote Control Technologies Pty Ltd. Images for illustration purposes only. Discover more @ rct-global.com